

# PRODUCT SHEET

# OpenFrame MediaScreen

## 3.5inch OpenFrame MediaScreen

ArtNr: AC-0350F

### MAIN FEATURES:

- AutoStart by plug in power-adapter
- 3.5inch LCD panel 320\*240 pixels
- Internal videoplayer 480P
- Plastic Housing for built-in purpose
- 3.5mm Jack output (optional)
- Thin housing
- Power adapter with 2.5meter cable
- Usage up to 14 hours per day
- Additional features for interactivity
  - => read more below in this productsheet!



### MAIN PURPOSE:

- Digital Signage Display /Advertisement Display
- Built-in ShopDisplays



### USAGE:

This MediaScreen has an Internal VideoPlayer. Plug in a SD card or USB Stick with your content and directly play your video (or slideshow). It will play your video(s) continously in a loop. The mainboard can optionally come with extra in-outputs for interactivity, see the options below.

### OPTIONAL: Multi Functions

The mainboard can be turned into a multi-functionboard, several in-outputs can be added, and software can be made Tailormade. Example features:

- External Speakers
- Trigger buttons for selection video / volume combined with LED lighting
- Output for LED lightning 5/12V
- Motion Sensor / Tilt-up light Sensor
- Multiple Audio Outputs for speakers & headphones
- Input Audio for Mobile phone / iPod (auto-sensing)
- Touchscreen
- Etcetera



Optional with interactive in-outputs

=> find more about the options below in this productsheet.



Next pages:  
additiononal features  
technical specs and drawing



**3.5inch Open Frame MediaScreen**

ArtNr: AC-035OF

**TECHNICAL SPECIFICATIONS**

Display	Panel	3.5inch LCD Media Player
	Shell	Open Frame - for built-in purpose
	Resolution	320*240
	Aspect Ratio	4:3
Interface	Card slot	SD Card
	USB Host	USB Host 2.0
	Power Jack	DC 12V/1.5A power input
	Head phone	3.5mm Jack output
Sound System	Speaker	Optional
VIDEO	Video format	1) AVI (XVID. H.264)
		2) MPEG-1 H.264
		3) MPEG 2 H.264
		4) MOV (XVID. H.264)
AUDIO	Audio format	MP3
PHOTO	Photo	JPEG
	Other	Automatic slide show playback Playback speed adjustment interval setup
Standard Functions	AutoStart	AUTO Start and repeat all file.
	Loop	Continuous loop demo video
Optional functions	Trigger Buttons	Push- and Touchbuttons, Press&Turn button
	Sensors	Motion sensor or Lift sensor to activate videos
	Speakers	External Speakers
	Batterybox	8D-Cell Batterybox for battery operated power
	Audio out	Multiple Jacks 3.5 / Coax / Digital Sound
	Jack Input	Jack Input for mobile phone / mp3-player sound
	Software	Software adjustments for your needs
	LED	LED strips, LED light pads
	Output Voltage	(multiple) Output 12V (5V), f.i. for LED lighting
	Touchscreen	Transistive TouchScreen
Others	Accessories:	Power Adapter
	Color:	Black Housing
	Brackets:	

PRODUCT SHEET

3.5inch Open Frame MediaScreen

ArtNr: AC-035OF

OpenFrame Mediascreen

DRAWING

